


# **TECHCONNECT**

## SITE PART AUDIT

## **SITE PARTS**


- You can view a list of parts, audit parts and do parts swap outs on the site you are currently working on.
- This functionality only works with **BPO\_V2**.
- The IsVersionBPO2 flag must be set to Yes in BPO Configurator.
- Click on the call / project you wish to work on.






- The *Call* screen will be displayed.
- Click on the *Side Menu*.





- A *Side Menu* will be displayed.
- Click on *Site Parts*.





- Assets that should be at the address according to **BPO** transactions are displayed in the **Site Parts List** screen showing the;
  - 1. the part description,
  - 2. part code,
  - 3. serial number,
  - 4. swap out icon,



- 5. missing part icon
- 6. and add part icon.





## **PARTS AUDIT**

#### MARK A PART AS MISSING


- If a part displayed on the part list is missing on site,
- click on the *Missing Part* icon to mark the part as missing.



Help v2.5.1.4 - Pg 6 - Printed: 27/06/2024




- A *Missing Part* message box will pop up asking you;
  - Are you sure this part is not on-site and should be marked as missing?
- Click on Yes.






• The part will now be marked as *Missing* in the *Site Parts List* screen.



#### **ADD A MISSING PART**

- If a part is not displayed on the part list but is on site,
- click on the *Add Part* icon to add the part.






- The Site Part screen will be displayed. You will either receive
  - 1. a message informing you;
    - Please download the parts list by going to the Parts section from the main menu and clicking on the reload icon.




• Click on *Cancel*. Refresh your parts database and start the process of adding a missing part again.




- 2. or a *Search* field will be displayed.
  - In the *Search* field, type in the part description or model of the part you wish to add.






- A list of part codes that match your description will be displayed.
- Click on the '+' icon on the part code you wish to add.





- 1. In the *Serial Number* field, type in the serial number of the part you wish to add.
- 2. Click on Add.






- You will return to the *Site Parts List* screen.
- The part will now be displayed in the *Site Parts List* screen.




## **SWAP OUTS**

- 1. Click on the *Swap Out* icon on the part you wish to swap out.
- 2. In this image, serial number *2020-00020* has been selected.



• The *Swap Part - []* screen will be displayed.






- 1. Type in the description or model of the replacement part.
  - A list of parts in your boot stock warehouse which match your description / model will be displayed.
- 2. Click on the '+' sign on the part you wish to add as a replacement.



• In this image, serial number *2020-7865GE* has been selected.



- 1. The details of the replacement item will be displayed.
- 2. Click on Swap.






- Note: If you try to swap out an item that is not linked to a contract, an *Alert* message in the *Site Parts List* screen will pop up telling you;
  - There is some configuration missing required for this swap out. Please contact your system



#### administrator.


• Click on *Ok* and make sure the item is linked to a contract.



 The part that was swapped out will no longer be displayed in the Site Parts List screen, it will now be in the Asset Warehouse in BPO.



• In this image, serial number *2020-00020* is no longer displayed in the *Site Parts List* screen.



• The replacement part will now be displayed in the *Site Parts List* screen.



• In this image, serial number *2020-7865GE* is now displayed in the *Site Parts List* screen.



MNU.150.007